

**FEATURES:**

- USE WITH V-2924A CONTROL UNIT
- FITS A SINGLE-GANG ELECTRICAL BOX
- BRUSHED STAINLESS STEEL WALL PLATE
- BLACK "CALL" BUTTON FOR NORMAL CALL
- RED "CALL" BUTTON FOR EMERGENCY CALLS
- BUILT-IN VOLUME CONTROL



**DESCRIPTION:**

The V-2971 (Call Switch) and the V-2970 (Emergency/Normal Call Switch with Volume Control) are designed to be used with the V-2924A and V-2925A Intercom Units. The V-2970 emergency button converts a single button press into the four switch closures required to generate an "Emergency" class of service call.

When the black button is pressed, the V-2971 produce a momentary closure for calling into the V-2924A. The V-2970 also provides an "Emergency" call-in signal (4 interrupted momentary closures) when the red button is pressed.

**Specifications:**

**SWITCH (V-2971)**

Single pole momentary pushbutton

**SWITCHES (V-2970)**

Black Single pole momentary pushbutton  
 "Normal Call"

Red Single pole momentary pushbutton with  
 electronic pulse generator "Emergency Call"

**ENVIRONMENT:**

Suitable for indoor installations

**HOUSING AND FINISH**

Brushed stainless steel single gang wall plate with black  
 screen printed text.

**DIMENSIONS AND WEIGHT:**

4.5 "H x 2.75 "W x 1.0 "D (11.43 cm x 6.985 cm x 2.54 cm)

Weight: 0.2 lbs ( 0.09 kg)

Shipping Weight: 0.35 lbs ( 0.1575 kg)

**MOUNTING**

Call button mounts in a single gang electrical box  
 using two screws

## **ARCHITECTS' AND ENGINEERS**

### **V-2971**

The call switch shall be a momentary pushbutton switch with a .5" square black plastic cap mounted on a brushed stainless steel plate. A screwdriver set volume control shall be provided to allow audio level adjustment of externally connected 45-ohm speakers. The unit shall be compatible with single gang electrical boxes.

Dimensions shall be 4.5 "H x 2.75 "W x 1.0 "D (11.43 cm x 6.985 cm x 2.54 cm) and the unit shall weigh 0.2 lbs (0.09 kg). The Call switch with volume control shall be Model Number V-2971.

### **V-2970**

The "Normal" call switch shall be a momentary pushbutton style switch with a .5" square Black plastic cap. The "Emergency" call switch shall be a momentary pushbutton style switch with a .5" square Red plastic cap. A pulse generator shall be provided as part of the call station to convert a single press of the red emergency button to the four closures, required to generate an "Emergency" Class of service call. The call station shall be line powered. A screwdriver set volume control shall be provided to allow audio level adjustment of externally connected 45-ohm speakers. The unit shall be compatible with single gang electrical boxes.

Dimensions shall be 4.5 "H x 2.75 "W x 1.0 "D (11.43 cm x 6.985 cm x 2.54 cm) and the unit shall weigh 0.2 lbs (0.09 kg). The Emergency Call station with volume control shall be Model Number V-2970.

## **LIMITED WARRANTY**

Valcom, Inc. warrants its products to be free from defects in materials and workmanship under conditions of normal use and service for a period of one year from the date of shipment. The obligation under this warranty shall be limited to the re-placement, repair or refund of any such defective device within the warranty period, provided that:

1. inspection by Valcom, Inc. indicates the validity of the claim,
2. the defect is not the result of damage, misuse, or negligence after the original shipment,
3. the product has not been in any way repaired by others and that factory sealed units are unopened (A service charge plus parts and labor will be applied to units defaced or physically damaged).
4. freight charges for the return of products to Valcom, Inc. are prepaid,
5. all units "out of warranty" are subject to a service charge. The service charge will cover minor repairs (major repairs will be subject to additional charges for parts and labor)

**This warranty is in lieu of and excludes all other warranties expressed or implied, and in no event shall Valcom, Inc. be liable for any anticipated profits, consequential damages, loss of time or other losses incurred by the buyer in connection with the purchase, operation or use of the product.**

This warranty specifically excludes damage incurred in shipment. In the event a product is received in damaged condition, the carrier should be notified immediately. Claims for such damage should be filed with the carrier involved in accordance with the F.O.B. point.