

FEATURES:

- 8" 5-WATT SPEAKER
- COMBINATION 25, 70V TRANSFORMER
- FIVE VOLUME SETTINGS

**DESCRIPTION:**

8-inch speaker with five volume settings. Operates on 25 or 70-volt speaker lines.

Specifications:**SPEAKER**

8" (20.32 cm)

VOICE COIL

8 ohm

SOUND PRESSURE LEVEL

95 dB at 1 Meter on Axis with 1 Watt Input at 1 kHz

LINE TRANSFORMER

Combination 25/70 Volt

TRANSFORMER TAPS

5, 2.5, 1.25, 0.625 and 0.312 Watts

ENVIRONMENT

Temperature: 0 to 50 °C (32 to 122 °F)

Humidity: 0-85% Non-Precipitating

DIMENSIONS AND WEIGHT

8.0" (20.3 cm) Dia. X 2.25" (5.7cm) D

Weight: 1.7 lbs. (0.77 kg)

Note: 25-Volt Speakers may be used as One-Way or Two-Way (talkback speakers). This functionality is determined by the equipment used to source audio to/from the speaker.

ARCHITECTS' AND ENGINEERS

The Model V-936400 speaker shall consist of an 8" (20.32 cm) speaker with a 25/70-volt transformer.

The speaker shall be 8" (20.32 cm) in diameter. The impedance of the speaker shall be 8-ohm. The speaker shall be capable of handling 5-watts continuous power. Sound pressure level at 1 meter on axis with 1-watt input shall be 95 dB. The frequency response shall be 65 Hz to 17 kHz.

The line transformer shall be capable of operating on a 25 or 70-volt line and provide 5 volume adjustments. The level adjustments shall range from .3 watts to 5 watts.

Weight shall be approximately 1.7 lbs (0.77 kg).

LIMITED WARRANTY

Valcom, Inc. warrants its products to be free from defects in materials and workmanship under conditions of normal use and service for a period of one year from the date of shipment. The obligation under this warranty shall be limited to the re-placement, repair or refund of any such defective device within the warranty period, provided that:

1. inspection by Valcom, Inc. indicates the validity of the claim,
2. the defect is not the result of damage, misuse, or negligence after the original shipment,
3. the product has not been in any way repaired by others and that factory sealed units are unopened (A service charge plus parts and labor will be applied to units defaced or physically damaged).
4. freight charges for the return of products to Valcom, Inc. are prepaid,
5. all units "out of warranty" are subject to a service charge. The service charge will cover minor repairs (major repairs will be subject to additional charges for parts and labor)

This warranty is in lieu of and excludes all other warranties expressed or implied, and in no event shall Valcom, Inc. be liable for any anticipated profits, consequential damages, loss of time or other losses incurred by the buyer in connection with the purchase, operation or use of the product.

This warranty specifically excludes damage incurred in shipment. In the event a product is received in damaged condition, the carrier should be notified immediately. Claims for such damage should be filed with the carrier involved in accordance with the F.O.B. point.